

# Hurricane Series

## Rally

### MicroRider Automatic Scrubbers



#### Innovative

Our machines are designed with innovative technologies to increase productivity while lowering the cost of cleaning. The intuitive control panel and superior maneuverability makes it easy to use for any operator.



#### Compact

The Rally is designed to clean the areas that are inaccessible with larger riders. It is small and easily maneuverable but yet offers a wide cleaning path for maximum productivity in your larger cleaning areas.



#### Easy Check

Easy for the operator to find the ordinary maintenance areas that are clearly indicated in yellow. It includes brushes with maximum consumption indicator.



Specifications	Rally 21	Rally 24	Rally 28
<b>Model Number</b>	19366-C-AGM	19367-C-AGM	19368-C-AGM
<b>Productivity (Theoretical at max speed)</b>	34,229 ft <sup>2</sup> /h (3180 m <sup>2</sup> /hr)	39,654 ft <sup>2</sup> /h (3684 m <sup>2</sup> /hr)	43,788 ft <sup>2</sup> /h (4068 m <sup>2</sup> /hr)
<b>Scrubbing Width</b>	21" (53 cm)	24" (61 cm)	27" (68 cm)
<b>Squeegee Width</b>	28" (71 cm)	37" (94 cm)	37" (94 cm)
<b>Numbers of Brushes</b>	1 x 21" (1 x 53 cm)	2 x 12" (2 x 30 cm)	2 x 14" (2 x 35.5 cm)
<b>Brush/Pad Speed</b>	215 rpm	285 rpm	285 rpm
<b>Brush Motor Power</b>	400 W	2 x 400 W	2x 400 W
<b>Motor Type</b>	2-stages (480 W)	3-stages (550 W)	3-stages (550 W)
<b>Water Lift at Squeegee</b>	48" (123 cm)	48" (123 cm)	48" (123 cm)
<b>Traction Motor</b>	Yes	Yes	Yes
<b>Solution Tank Capacity</b>	21 Gal (80 L)	21 Gal (80 L)	21 Gal (80 L)
<b>Recovery Tank Capacity</b>	22 Gal (83 L)	22 Gal (83 L)	22 Gal (83 L)
<b>Power Supply</b>	24 V (4 x 6 V)	24 V (4 x 6 V)	24 V (4 x 6 V)
<b>Maximum Speed</b>	6 km/h	6 km/h	6 km/h
<b>Weight (Without Batteries)</b>	260 lbs (118 kg)	377 lbs (171 kg)	401 lbs (182 kg)
<b>Unit Size (LxWxH)</b>	52" x 26" x 41" (131 x 67 x 103 cm)	52" x 26" x 41" (131 x 67 x 103 cm)	52" x 26" x 41" (131 x 67 x 103 cm)
<b>Run Time</b>	4-4.5 hrs	4-4.5 hrs	4-4.5 hrs
<b>Noise Level</b>	65 dB	65 dB	65 dB
<b>Approval(s)</b>	N/A	N/A	N/A